



# CellAdvisor™

## JD786B RF Analyzer



### Spectrum Analyzer (standard)

Frequency		
Frequency range	9 kHz to 8 GHz	
Internal 10 MHz Frequency Reference		
Accuracy	±0.05 ppm + aging (0 to 50°C)	
Aging	±0.5 ppm/year	
Frequency Span		
Range	0 Hz (zero span) 10 Hz to 8 GHz	
Resolution	1 Hz	
Resolution Bandwidth (RBW)		
–3 dB bandwidth	1 Hz to 3 MHz	1-3-10 sequence
Accuracy	±10% (nominal)	
Video Bandwidth (VBW)		
–3 dB bandwidth	1 Hz to 3 MHz	1-3-10 sequence
Accuracy	±10% (nominal)	
Single Sideband (SSB) Phase Noise		
Fc 1 GHz, RBW 10 kHz, VBW 1 kHz, RMS detector		
<b>Carrier Offset:</b>		
30 kHz	–100 dBc/Hz (–102 dBc/Hz, typical)	
100 kHz	–105 dBc/Hz (–112 dBc/Hz, typical)	
1 MHz	–115 dBc/Hz (–120 dBc/Hz, typical)	
Measurement Range		
	DANL to +25 dBm	
Input attenuator range	0 to 55 dB, 5 dB steps	
Maximum Input Level		
Average continuous power	+25 dBm	
DC voltage	±50 V DC	

\*All specifications are subject to change without notice.

**Spectrum Analyzer: 9 kHz to 8 GHz**

**Cable and Antenna Analyzer: 5 MHz to 6 GHz**

**Power Meter: 10 MHz to 8 GHz**

### Specification\* Conditions

The JD786B specifications apply under these conditions:

- The instrument has been turned on for at least 15 minutes
- The instrument is operating within a valid calibration period
- Data with no tolerance are considered typical values
- Cable and antenna measurements apply after calibration to the OSL standard
- Typical and nominal values are defined as:
  - Typical: expected performance of the instrument operating at 20 to 30°C after being at this temperature for 15 minutes
  - Nominal: a general, descriptive term or parameter

Displayed Average Noise Level (DANL)		
1 Hz RBW, 1 Hz VBW, 50 Ω termination, 0 dB attenuation, RMS detector		
<b>Preamplifier Off</b>		
10 MHz to 3 GHz	–140 dBm (–145 dBm, typical)	
>3 GHz to 5 GHz	–138 dBm (–142 dBm, typical)	
>5 GHz to 7 GHz	–135 dBm (–138 dBm, typical)	
>7 GHz to 8 GHz	–132 dBm (–135 dBm, typical)	
<b>Preamplifier On</b>		
10 MHz to 3 GHz	–160 dBm (–165 dBm, typical)	
>3 GHz to 5 GHz	–158 dBm (–162 dBm, typical)	
>5 GHz to 7 GHz	–155 dBm (–158 dBm, typical)	
>7 GHz to 8 GHz	–152 dBm (–155 dBm, typical)	
Display Range		
Log scale and units (10 divisions displayed)	1 to 20 dB/division in 1 dB steps dBm, dBV, dBmV, dBμV	
Linear scale and units (10 divisions displayed)	V, mV, mW, W	
Detectors	Normal, positive peak, sample, negative peak, RMS	
Number of traces	6	
Trace functions	Clear/write, maximum hold, minimum hold, capture, load view on/off	
Total Absolute Amplitude Accuracy		
Preamplifier off, power level >–50 dBm, auto-coupled		
1 MHz to 8 GHz	±1.3 dB (±0.5 dB typical)	20 to 30°C
	Add ±1.0 dB	–10 to 55°C after 60-minute warm up
Reference Level		
Setting range	–120 to +100 dBm	
<b>Setting Resolution</b>		
Log scale	0.1 dB	
Linear scale	1% of reference level	
Markers		
Marker types	Normal, delta, delta pair, noise, frequency count marker	
Number of markers	6	
Marker functions	Peak, next peak, peak left, peak right, minimum search marker to center/start/stop	
RF Input VSWR		
1 MHz to 8 GHz	1.5:1 (typical)	Atten >20 dB
Second Harmonic Distortion		
Mixer level	–25 dBm	
50 MHz to 2.6 GHz	<–65 dBc (typical)	
>2.6 GHz to 8 GHz	<–70 dBc (typical)	

Third-Order Inter-Modulation (third-order intercept: TOI)		
200 MHz to 3 GHz	+10 dBm (typical)	
>3 GHz to 8 GHz	+12 dBm (typical)	
Spurious		
Inherent residual response		
Input terminated, 0 dB attenuation, preamplifier off, RBW at 10 kHz, Sweep mode	−90 dBm (nominal)	
Exceptions	−85 dBm at 164.1 MHz, 2.57264, 3.2, and 4.5 GHz −80 dBm at 4.8/7.8 GHz −75 dBm at 85.6 MHz and 428 MHz −70 dBm at 256.8 MHz and 770.4 MHz	
Input-related spurious	< −70 dBc (nominal)	
Dynamic Range		
2/3 (TOI-DANL) in 1 Hz RBW	>104 dB	at 2 GHz
Sweep Time		
Range	0.4 ms to 1000 s 24 μs to 200 s	Span = 0 Hz (zero span)
Accuracy	±2%	Span = 0 Hz (zero span)
Mode	Continuous, single	
Gated Sweep		
Trigger source	External, video, and GPS	
Gate length	1 μs to 100 ms	
Gate delay	0 to 100 ms	
Trigger		
Trigger source	Free run, video, external	
Trigger Delay		
Range	0 to 200 s	
Resolution	6 μs	
Measurements*		
Channel power		
Occupied bandwidth		
Spectrum emission mask		
Adjacent channel power		
Spurious emissions		
Field strength		
AM/FM audio demodulation		
Route map		
PIM detection		
Dual spectrum		

\* High-Power CW Signal Generator (Option 003) can be set up simultaneously.

## Cable and Antenna Analyzer (standard)

Frequency	
Range	5 MHz to 6 GHz
Resolution	10 kHz
Accuracy	±1 ppm
Data Points	
126, 251, 501, 1001, 2001	
Measurement Speed	
Reflection/DTF	1.0 ms/point (typical)
Measurement Accuracy	
Corrected directivity	40 dB
Reflection uncertainty	±(0.3 +  20log (1+10-EP/20) ) (typical) EP = directivity – measured return loss
Output Power	
High	5 MHz to 5.5 GHz, 0 dBm (typical) 5.5 GHz to 6 GHz, –5 dBm (typical)
Low	5 MHz to 6 GHz, –30 dBm (typical)
Dynamic Range	
Reflection	60 dB
Maximum Input Level	
Average continuous power	+25 dBm (nominal)
DC voltage	±50 V DC
Interference Immunity	
On channel	+17 dBm at >1.4 MHz from carrier frequency (nominal)
On frequency	0 dBm within ±10 kHz from the carrier frequency (nominal)
Measurements	
<b>Reflection (VSWR)</b>	
VSWR range	1 to 65
Return loss range	0 to 60 dB
Resolution	0.01
<b>Distance to Fault (DTF)</b>	
Vertical VSWR range	1 to 65
Vertical return loss range	1 to 60 dB
Vertical resolution	0.01
Horizontal range	0 to (# of data points – 1) x horizontal resolution Maximum = 1500 m (4921 ft) (1.5 x 108) x (V <sub>p</sub> )/delta V <sub>p</sub> = propagation velocity Delta = stop freq – start freq (Hz)
Horizontal resolution	
<b>Cable Loss (1-Port)</b>	
Range	0 to 30 dB
Resolution	0.01 dB
<b>1-Port Phase</b>	
Range	–180 to +180°
Resolution	0.01°
<b>Smith Chart</b>	
Resolution	0.01

## RF Power Meter (standard)

General Parameters			
Display range	100 to +100 dBm		
Offset range	0 to 60 dB		
Resolution	0.01 dB or 0.1 x W (x = m, u, p)		
Internal RF Power Sensor			
Frequency range	10 MHz to 8 GHz		
Span	1 kHz to 100 MHz		
Dynamic range	-120 to +25 dBm		
Maximum power	+25 dBm		
Accuracy	Same as spectrum analyzer		
External RF Power Sensors			
Directional	JD731B	JD733A	
Frequency range	300 MHz to 3.8 GHz	150 MHz to 3.5 GHz	
Dynamic range	0.15 to 150 W (average) 4 to 400 W (peak)	0.1 to 50 W (average) 0.1 to 50 W (peak)	
Connector type	Type-N female on both ends		
Measurement type	Forward/reverse average power, forward peak power, VSWR		
Accuracy	±(4% of reading + 0.05 W) <sup>1,2</sup>		
Terminating	JD732B	JD734B	JD736B
Frequency range	20 MHz to 3.8 GHz		
Dynamic range	-30 to +20 dBm		
Connector type	Type-N male		
Measurement type	Average	Peak	Average and peak
Accuracy	±7% <sup>1</sup>		

## Optical Power Meter (Standard)

Optical Power Meter		
Display range	-100 to +100 dBm	
Offset range	0 to 60 dB	
Resolution	0.01 dB or 0.1 mW	
External Optical Power Sensors		
	MP-60A	MP-80A
Wavelength range	780 to 1650 nm	
Max permitted input level	+10 dBm	+23 dBm
Connector type	Type-N female on both ends	
Connector input	Universal 2.5 and 1.25 mm	
Accuracy	±5%	

1. CW condition at 25°C ±10°C

2. Forward power

## 2-Port Transmission Measurements (Option 001)

Frequency		
Frequency range	5 MHz to 6 GHz	
Frequency resolution	10 kHz	
Output Power		
High	5 MHz to 5.5 GHz, 0 dBm (typical) 5.5 GHz to 6 GHz, −5 dBm (typical)	
Low	5 MHz to 6 GHz, −30 dBm (typical)	
Measurement Speed		
Vector	1.6 ms/point (typical)	
Scalar	3.4 ms/point (typical)	
Dynamic Range		
Vector	5 MHz to 3 GHz, 80 dB >3 GHz to 6 GHz, 75 dB	at average 5 at average 5
Scalar	5 MHz to 4.5 GHz, >110 dB 4.5 GHz to 6 GHz, >105 dB	
Measurements		
Insertion Loss/Gain		
Range	−120 to 100 dB	
Resolution	0.01 dB	
2-Port Phase		
Range	−180 to +180°	
Resolution	0.01°	

## Bias-Tee (Option 002)

Voltage	
Voltage range	+12 to +32 V
Voltage resolution	0.1 V
Power	
8 W Max	

## High Power CW Signal Generator (Option 003)

Frequency	
Frequency range	10 MHz to 5500 MHz
Frequency reference	<±1 ppm maximum
Frequency resolution	10 kHz
Output Power	
Range	10 MHz to 3.5 GHz, –60 to +10 dBm 3.5 GHz to 5.5 GHz, –60 to +5 dBm
Step	1 dB
Accuracy	±1.5 dB (20 to 30°C)

## GPS Receiver and Antenna (Option 010)

GPS Indicator		
	Latitude, longitude, altitude	
High-Frequency Accuracy		
Spectrum, interference, and signal analyzer		
GPS lock	±25 ppb	
Hold over (for 3 days)	±50 ppb (0 to 50°C)	15 minutes after satellite locked
Connector	SMA, female	

## Interference Analyzer (Option 011)

Measurements	
Spectrum analyzer	Sound indicator, AM/FM audio demodulation, interference ID, spectrum recorder
Spectrogram	Collect up to 72 hours of data
RSSI	Collect up to 72 hours of data
Interference finder	
Spectrum replayer	
Dual spectrogram	

## Channel Scanner (Option 012)

Frequency Range	
	1 MHz to 8 GHz
Measurement Range	
	110 to +25 dBm
Measurements	
Channel scanner	1 to 20 channels
Frequency scanner	1 to 20 frequencies
Custom scanner	1 to 20 channels or frequencies

## Bluetooth Connectivity (Option 013)

Personal Area Network (PAN)
File Transfer Profile (FTP)

## Wi-Fi Connectivity (Option 016)

Interface type	USB LAN Card
Interface standard	IEEE 802.11 b/g/n
Chipset	RealTek, Ralink
USB wireless mode	Infrastructure mode
Web-based remote control	Internet Explorer, Chrome, Safari
Internet protocol version	IPv4, IPv6

EMF Analyzer (Option 050)

General Parameters		
Supported Antenna	Isotropic Antenna G700050380 26 MHz to 3 GHz	
Mode	Sweep / FFT	
Trace	X-Axis, Y-Axis, Z-Axis, Current, Isotropic, Isotropic Accumulated	
Limit lines	MSL, ICNIRP	
Dwell Time	1 to 60s	
Measurement Time	1 to 30 min (# of measurement = Measurement Time / (Dwell Time x 3)	
Units	dBµV/m, dBmV/m, dBV/m, V/m, W/m², dBm/m², dBW/m², A/m, dBA/m, and Watt/cm².	
Miscellaneous	Spectrum logging and Replay Export to CSV PDF Report Generation	
Measurement		
Option 050 and G700050380		
Trace: X-Axis, Y-Axis, Z-Axis, Current, Isotropic, Isotropic Accumulated	Isotropic EMF Power: AVG, Max, Min	Accumulated Isotropic EMF Power: AVG, Max, Min

## RFoCPRI/Interference Analyzer (Option 008, 060, 061, 062, 063, 064, and 065)

General Parameters					
Optical interface		Dual SFP/SFP+ (supports all MSA compliant SFP modules)			
Line rates	614.4 Mbps (1x) , 1228.8 Mbps (2x)		Option 008 and 060		
	2457.6 Mbps (4x)		Option 008 and 061		
	3072.0 Mbps (5x)		Option 008 and 062		
	4915.2 Mbps (8x)		Option 008 and 063		
	6144.0 Mbps (10x)		Option 008 and 064		
	9830.4 Mbps (16x)		Option 008 and 065		
Resolution Bandwidth (RBW)					
–3 dB bandwidth		1 kHz to 10 kHz (span ≤ 3.84 MHz) 1 KHz to 100 kHz (3.84 MHz < span < 30.86 MHz)		1-3-10 sequence	
Accuracy		±10% (nominal)			
VBW					
–3 dB bandwidth		1 Hz to 100 KHz		1-3-10 sequence	
Accuracy		±10% (nominal)			
CPRI Parameter					
IQ Sample width		4 – 20 (step 1)			
Mapping method		1 and 3			
TX clock		Internal/external/recovered			
Port type		Master/slave			
Map position		AxC#0 – AxC#7			
Bandwidth		1.4 MHz, 3 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz			
Measurements					
Layer-2 Monitoring		Layer-2 Term		Interference analyzer	
Port 1	Port 2	Port 1 or 2 (exclusive)		Spectrum	Sound indicator, AM/FM audio demodulation, interference ID, spectrum recorder
LOS	LOS	LOS	SDI		
LOF	LOF	LOF	RAI		
SDI	SDI	Optic RX level	dBm		
RAI	RAI	Protocol version	1 to 10	Spectrogram	Collect up to 72 hr of data
Optic RX level	Optic RX level	C and M HDLC rate (kbps)	No HDLC, 240, 480, 960, 1920, 2400	RSSI	Collect up to 72 hr of data
SFP Information	SFP Information			Spectrum replay	X1, x2, x4, x8
Wavelength	Wavelength	C and M Ethernet subchannel number	20 to 63	PIM Detection	
Vendor	Vendor			Single carrier	
Vendor PN	Vendor PN	Alarm Injection			Multi carrier
Vendor rev	Vendor rev	R-LOS	Single	PIM calculator	
Power level type	Power level type	R-LOF	Single		
Diagnostic byte	Diagnostic byte	Error Injection			
Nominal rate	Nominal rate	Code	Single/rate		
Min rate	Min rate	K30.7	Single/rate		
Max RX level	Max RX level	Error rate	1E-3 to 1E-9		
Max TX level	Max TX level				

## RFoBSAI™ Interference Analyzer (Option 070, 071, 072, 073)

General Parameters					
Optical interface		Dual SFP/SFP+ (supports all MSA compliant SFP modules)			
Line rates	768 Mbps (1x)		Option 070		
	1536 Mbps (2x)		Option 071		
	3072 Mbps (4x)		Option 072		
	6144 Mbps (8x)		Option 073		
Resolution Bandwidth (RBW)		1 kHz to 10 kHz (span ≤ 3.84 MHz) 1 KHz to 100 kHz (3.84 MHz < span ≤ 30.86 MHz)			
		Accuracy	±10% (nominal)		
Video Bandwidth (RBW)		1 Hz to 100 KHz			
		Accuracy	±10% (nominal)		
RP3 Type		LTE (FDD/TDD), UMTS (FDD)			
RP3 Address		Hexadecimal			
TX clock		Internal/external/recovered			
Port type		Master/slave			
Bandwidth		LTE-FDD/TDD: 1.4 MHz, 3 MHz, 5 MHz, 10 MHz, 15 MHz, 20 MHz UMTS: 3MHz for downlink, 5MHz for Uplink			
RP3 Address List		RP3 Address, Technology, Scrambler seed*, Message Count*			
Scrambler Seed		Nx7 Index: 0 – 17, step 1			
Measurements					
Layer-2 Monitoring		Layer-2 Term		Interference analyzer	
Port 1	Port 2	Port 1 or 2 (exclusive)		Spectrum	Sound indicator, AM/FM audio demodulation, interference ID, spectrum recorder
LOS	LOS	LOS			
LOF	LOF	LOF			
Code Violation	Code Violation	Optic RX level	dBm	Spectrogram	Collect up to 72 hr of data
K30.7 words	K30.7 words	Optic TX level	dBm		
Optic RX level	Optic RX level	Port Type	Master		
Optic TX level	Optic TX level	TX State	State machine	RSSI	Collect up to 72 hr of data
Messages Address	Message Address	RX State	State machine	Spectrum replay	X1, x2, x4, x8
Message Counter	Message Counter	TX Address	RP3 Address (Hexadecimal)		
<b>SFP Information</b>	<b>SFP Information</b>	RX Address	RP3 Address (Hexadecimal)	PIM Detection	Single carrier Multi carrier PIM calculator
Wavelength	Wavelength	Word Sync Loss Event			
Vendor	Vendor	Code Violation			
Vendor PN	Vendor PN	K30.7 words			
Vendor rev	Vendor rev	Frame Sync Loss Events			
Power level type	Power level type	<b>Alarm Injection</b>			
Diagnostic byte	Diagnostic byte	K30.7	Single		
Nominal rate	Nominal rate	<b>Error Injection</b>			
Min rate	Min rate	Code	Single/rate		
Max RX level	Max RX level	Error rate	1E-3 to 1E-9		
Max TX level	Max TX level				

\* Available only when the link rate is 61Gbps

## RFoCPRI™ LTE-FDD Signal Generator (Option 081)

General Parameters		
Optical interface	Dual SFP/SFP+ (supports all MSA compliant SFP modules)	
Link Rate	614.4 Mbps (1x), 1228.8 Mbps (2x), 2457.6 Mbps (4x), 3072.0 Mbps (5x), 4915.2 Mbps (8x), 6144.0 Mbps (10x), 9830.4 Mbps (16x)	
IQ Sample width	8 – 20 bits	
Mapping method	Packed and Flexible	
Waveform	Off: CW On: LTE-FDD E-TM1.1, E-TM1.2, E-TM2, E-TM3.1, E-TM3.2, E-TM3.3	
Bandwidth	5 MHz, 10MHz, 15MHz, 20MHz	
Sampling Frequency	N x 3.84MHz (N=2, 4, 6, 8)	
Gain dynamic range	0 to -50 dB	
Frequency error	±10 Hz + ref freq accuracy	99% confidence level
Residual EVM (RMS)	0.2% (typical)	Data EVM

## RFoCPRI™ LTE-TDD Signal Generator (Option 082)

General Parameters		
Optical Hardware (Option 008)		
Interface	Two SFP/SFP+ ports (supports all MSA compliant SFP modules), One Ethernet port	
CPRI Parameter		
Line coding	8B/10B	
Line rates	614.4 Mbps, 1228.8 Mbps (Option 060) 2457.6 Mbps (Option 061) 3072.0 Mbps (Option 062)	4915.2 Mbps (Option 063) 6144.0 Mbps (Option 064) 9830.4 Mbps (Option 065)
CPRI Parameter		
IQ Sample width	4 – 20 (step 1)	
Mapping method	1 and 3	
Waveform	CW, LTE-TDD E-TM1.1, E-TM1.2, E-TM2, E-TM3.1, E-TM3.2, E-TM3.3	
Bandwidth	5 MHz, 10 MHz, 15 MHz, 20 MHz	
Sampling Frequency	N x 3.84 MHz (N=2, 4, 6, 8)	
Gain dynamic range	0 to –50 dB	
Frequency error	±10 Hz + ref freq accuracy, 99% confidence level	
Residual EVM (RMS)	0.02% (typical), Data EVM	

## RFoOBSAI™ LTE-FDD Signal Generator (Option 086)

General Parameters		
Optical Hardware (Option 008)		
Interface	Two SFP/SFP+ ports (supports all MSA compliant SFP modules), One Ethernet port	
OBSAI Parameter		
Line coding	8B/10B	
Line rates	768 Mbps (Option 070) 1536 Mbps (Option 071)	3072 Mbps (Option 072) 6144 Mbps (Option 073)
CPRI Parameter		
RP3 Type	LTE	
RP3 Address	Hexadecimal	
Waveform	CW, LTE-FDD E-TM1.1, E-TM1.2, E-TM2, E-TM3.1, E-TM3.2, E-TM3.3	
Bandwidth	5 MHz, 10 MHz, 15 MHz, 20 MHz	
Sampling Frequency	N x 3.84 MHz (N=2, 4, 6, 8)	
Gain dynamic range	0 to –50 dB	
Frequency error	±10 Hz + ref freq accuracy, 99% confidence level	
Residual EVM (RMS)	0.02% (typical), Data EVM	



## RFoCPRI BBU Emulation for Alcatel-Lucent (Option 101)

General Parameters			
Optical Hardware (Option 008)			
Interface	Two SFP/SFP+ ports (supports all MSA compliant SFP modules), One Ethernet port		
CPRI Parameter			
Line coding	8B/10B		
Line rates	614.4 Mbps, 1228.8 Mbps (Option 060) 2457.6 Mbps (Option 061) 3072.0 Mbps (Option 062)	4915.2 Mbps (Option 063) 6144.0 Mbps (Option 064) 9830.4 Mbps (Option 065)	
Resolution Bandwidth (RBW)			
–3 dB bandwidth	1 kHz to 10 kHz (span ≤ 3.84 MHz) 1 KHz to 100 kHz (3.84 MHz < span ≤ 30.86 MHz)		
Accuracy	±10% (nominal)		
CPRI Parameter			
IQ Sample width	4 – 20 (step 1)		
Mapping method	1 and 3		
TX clock	Internal/External		
Port type	Master		
Bandwidth	5 MHz, 10 MHz, 15 MHz, 20 MHz		
Span	Adjustable (Max Span= Sampling Frequency)		
Measurements			
Carrier Configuration	SFP Information	Spectrum Clearance	Coverage Range
RRH Description	RRH Description	Spectrum	Spectrum
Carrier Information	SFP Information	Spectrogram	Carrier Information
CPRI & Active SW	Profile Editor	RSSI	VSWR
RRH Description		Dual Spectrum	Tilt
CPRI State		Dual Active Trace	PIM Analysis
Active SW		Dual Spectrogram	Single Radio
			Spectrum
			Flatness

## General Information

Inputs and Outputs		
<b>RF in</b> Connector Impedance Damage level	Spectrum analyzer Type-N, female 50 $\Omega$ (nominal) >+33 dBm, $\pm$ 50 V DC (nominal), 3 min	
<b>Reflection/RF out</b> Connector Impedance Damage level	Cable and antenna analyzer Type-N, female 50 $\Omega$ (nominal) >+40 dBm, $\pm$ 50 V DC (nominal), 3 min	
<b>RF in</b> Connector Impedance Damage level	Cable and antenna analyzer Type-N, female 50 $\Omega$ (nominal) >+25 dBm, $\pm$ 50 V DC (nominal)	
<b>External trigger, GPS</b> Connector Impedance	SMA, female 50 $\Omega$ (nominal)	
<b>External ref</b> Connector Impedance Input frequency Input range	SMA, female 50 $\Omega$ (nominal) 10 MHz, 13 MHz, 15 MHz -5 to +5 dBm	
<b>USB</b> USB host <sup>1</sup> USB client <sup>2</sup>	Type A, 1 port Type B, 1 port	
<b>SFP Cage</b> Port 1 Port 2	RFoFiber (with option 008) SFP/SFP+ compatible	
LAN	RJ45, 10/100Base-T	
Audio jack	3.5 mm headphone jack	
External power	5.5 mm barrel connector	
Speaker	Built-in speaker	
Display		
Type	Resistive touch screen	
Size	8 inch, LED backlight, transfective LCD with anti-glare coating	
Power		
External DC input	18 to 19 V DC	
Power consumption	42 W	54 W maximum (when charging battery)
Battery		
Type	10.8 V, 7800 mA/hr (Lithium ion)	
Operating time	>3 hr (typical) >1.4 hr (RFoCPRI)	
Charge time	3 hr (while not operating) 9 hr (while operating)	
Charging temperature	0 to 45°C (32 to 104°F) $\leq$ 85% RH	
Discharging temperature	-20 to 55°C (4 to 131°F) $\leq$ 85% RH	
Storage temperature <sup>3</sup>	0 to 25°C (32 to 77°F)	

Data Storage	
Internal <sup>4</sup>	Maximum 512 MB
External <sup>5</sup>	Limited by size of USB flash drive
Environmental	
Operating Temperature	
AC Power	0 to 40°C (32 to 104°F) with no derating
Battery	0 to 40°C (32 to 104°F) at charging -10 to 55°C (14 to 131°F) at discharging -10 to 50°C (14 to 122°F) at discharging with Option 008
Maximum humidity	95% RH (noncondensing)
Shock and vibration	MIL-PRF-28800F class 2
Storage temperature <sup>6</sup>	-30 to 71°C (-22 to 160°F)
EMC	
IEC/EN 61326-1:2006 (complies with European EMC)	
CISPR11:2009 +A1:2010	
ESD	
IIEC/EN 61000-4-2	
Size and Weight (standard configuration)	
Weight (with battery)	<4.4 kg (9.7 lb)
Size (W x H x D)	295 x 195 x 82 mm
Warranty	
3 years	
Calibration Cycle	
1 year	

1. Connects flash drive and power sensor.
2. Connects to PC for data transfer.
3. 20 to 85% RH, store battery pack in low-humidity environment; extended exposure to temperature above 45°C could significantly degrade battery performance and life.
4. Up to 3800 traces.
5. Supports USB 2.0 compatible memory devices.
6. With the battery pack removed

## Ordering Information

Description	Part Number
<b>Standard CellAdvisor Base Station Analyzer</b>	
Base station analyzer includes: · Spectrum analyzer 9 kHz to 8 GHz · RF power meter 10 MHz to 8 GHz · Cable and antenna 5 MHz to 6 GHz	JD786B <sup>1,2</sup>
<b>Options</b>	
Note: Upgrade options for the JD786B use the designation JD786BU before the respective last three-digit option number	
2 Port transmission measurements for JD786B <sup>3</sup>	JD786B001
Bias Tee for JD786B <sup>4</sup>	JD786B002
CW signal generator for JD786B	JD786B003
Optical hardware for JD786B <sup>5</sup>	JD786B008
GPS receiver and antenna for JD786B	JD786B010
Interference analyzer for JD786B <sup>6,7</sup>	JD786B011
Channel scanner for JD786B	JD786B012
Bluetooth connectivity for JD786B <sup>8</sup>	JD786B013
Wi-Fi connectivity for JD786B <sup>9</sup>	JD786B016
EMF analyzer for JD786B <sup>10</sup>	JD786B050
RFoCPRI 614M & 1.2G interference analyzer for JD786B <sup>11,12</sup>	JD786B060
RFoCPRI 2.4G interference analyzer for JD786B <sup>11,12</sup>	JD786B061
RFoCPRI 3.1G interference analyzer for JD786B <sup>11,12</sup>	JD786B062
RFoCPRI 4.9G interference analyzer for JD786B <sup>11,12</sup>	JD786B063
RFoCPRI 6.1G interference analyzer for JD786B <sup>11,12</sup>	JD786B064
RFoCPRI 9.8G interference analyzer for JD786B <sup>21,22</sup>	JD786B065
RFoBSAI 768M Interference analyzer for JD786B <sup>11,12</sup>	JD786B070
RFoBSAI 1.5G interference analyzer for JD786B <sup>11,12</sup>	JD786B071
RFoBSAI 3.1G interference analyzer for JD786B <sup>11,12</sup>	JD786B072
RFoBSAI 6.1G interference analyzer for JD786B <sup>11,12</sup>	JD786B073
RFoCPRI LTE-FDD signal generator for JD786B <sup>11,12,13</sup>	JD786B081
RFoCPRI LTE-TDD signal generator for JD786B <sup>11,12,13</sup>	JD786B082
RFoBSAI LTE-FDD signal generator for JD786B <sup>11,12,13</sup>	JD786B086
ALU BBU emulation for JD786B <sup>11,12</sup>	JD786B101
2 port transmission measurements floating license for JD740B/JD780B	JD780B001-FL
GPS receiver and antenna floating license for JD740B/JD780B	JD780B010-FL
Interference analyzer floating license for JD740B/JD780B	JD780B011-FL
Channel scanner floating license for JD740B/JD780B	JD780B012-FL
Bluetooth connectivity floating license for JD740B/JD780B	JD780B013-FL
Wi-Fi connectivity floating license for JD740B/JD780B	JD780B016-FL
EMF analyzer floating license for JD740B/JD780B	JD780B050-FL
RFoCPRI 614M & 1.2G interference analyzer floating license for JD740B/JD780B	JD780B060-FL
RFoCPRI 2.4G interference analyzer floating license for JD740B/JD780B	JD780B061-FL

Description	Part Number
RFoCPRI 3.1G interference analyzer floating license for JD740B/JD780B	JD780B062-FL
RFoCPRI 4.9G interference analyzer floating license for JD740B/JD780B	JD780B063-FL
RFoCPRI 6.1G interference analyzer floating license for JD740B/JD780B	JD780B064-FL
RFoCPRI 9.8G interference analyzer floating license for JD740B/JD780B	JD780B065-FL
RFoBSAI 768M interference analyzer floating license for JD740B/JD780B	JD780B070-FL
RFoBSAI 1.5G interference analyzer floating license for JD740B/JD780B	JD780B071-FL
RFoBSAI 3.1G interference analyzer floating license for JD740B/JD780B	JD780B072-FL
RFoBSAI 6.1G interference analyzer floating license for JD740B/JD780B	JD780B073-FL
RFoCPRI LTE-FDD signal generator floating license for JD740B/JD780B	JD780B081-FL
RFoCPRI LTE-TDD signal generator floating license for JD740B/JD780B	JD780B082-FL
RFoBSAI LTE-FDD signal generator floating license for JD740B/JD780B	JD780B086-FL
ALU BBU emulation floating license for JD740B/JD780B	JD780B101-FL

### Optional Accessories

#### Accessory - RF Calibrators (General)

Y- calibration kit Type-N(m), DC to 4 GHz, 50 ohm	JD72450509
Y- calibration kit DIN(m), DC to 4 GHz, 50 ohm	JD72450510
Y- calibration kit Type-N(m), DC to 6 GHz, 50 ohm	JD78050509
Y- calibration kit DIN(m), DC to 6 GHz, 50 ohm	JD78050510
EZ-Cal kit Type-N(m), DC to 6 GHz, 50 ohm	JD70050509
Dual port Type-N 4 GHz calibration kit	JD71050507
Dual port DIN 4 GHz calibration kit	JD71050508
Dual port Type-N 6 GHz calibration kit	JD78050507
Dual port DIN 6 GHz calibration kit	JD78050508
50 ohm Load, DC to 4 GHz, 1 W	GC72550511

#### Accessory - RF Cables (Cables)

RF cable DC to 8 GHz Type-N(m) to Type-N(m), 1.0 m	G700050530
RF cable DC to 8 GHz Type-N(m) to Type-N(f), 1.5 m	G700050531
RF cable DC to 8 GHz Type-N(m) to Type-N(f), 3.0 m	G700050532
RF cable DC to 18 GHz Type-N(m) to SMA(m), 1.5 m	G710050533
RF cable DC to 18 GHz Type-N(m) to QMA(m), 1.5 m	G710050534
RF cable DC to 18 GHz Type-N(m) to SMB(m), 1.5 m	G710050535
RF cable DC to 6 GHz Type-N(m) to DIN(f), 1.5 m	G710050536
RF cable DC to 4 GHz Type-N(m) to 1.0/2.3 (m), 1.5 m	G710050537
Phase-stable RF cable w grip DC to 6 GHz Type-N(m) to Type-N(f), 1.5 m	G700050540
Phase-stable RF cable w grip DC to 6 GHz Type-N(m) to DIN(f), 1.5 m	G700050541
RF cable DC to 18 GHz Type-N(m) to Type-N(f), 1.5 m	G710050531

## Ordering Information (Continued)

Description	Part Number
<b>Accessory - Optic Cables (Cables)</b>	
SM/LC T-Jumper and 1.5 m fiber cable <sup>15</sup>	G700050401
MM/LC T-Jumper and 1.5 m fiber cable <sup>15</sup>	G700050402
<b>Accessory - RF Antennas (General)</b>	
RF omni antenna Type-N(m), 806 to 896 MHz <sup>16</sup>	G700050353
RF omni antenna Type-N(m), 870 to 960 MHz <sup>16</sup>	G700050354
RF omni antenna Type-N(m), 1710 to 2170 MHz <sup>16</sup>	G700050355
RF omni antenna Type-N(m), 720 to 800 MHz <sup>16</sup>	G700050356
RF omni antenna Type-N(m), 2300 to 2700 MHz <sup>16</sup>	G700050357
Mag mount RF omni antenna Type-N(m), 689 to 1200 MHz, 1700 to 2700 MHz, 3000 to 6000 MHz <sup>16</sup>	G700050358
RF yagi antenna Type-N(f), 1750 to 2390 MHz, 10.2 dBd <sup>16, 17</sup>	G700050363
RF yagi antenna Type-N(f), 806 to 896 MHz, 10.2 dBd <sup>16, 17</sup>	G700050364
RF yagi antenna Type-N(f), 866 to 960 MHz, 9.8 dBd <sup>16, 17</sup>	G700050365
RF yagi antenna SMA(f), 700 to 4000 MHz, 1.85 dBd <sup>16, 17</sup>	G700050366
RF yagi antenna SMA(f), 700 to 6000 MHz, 2.85 dBd <sup>16, 17</sup>	G700050367
Isotropic Antenna Type-N(m), 26 MHz to 3 GHz <sup>18</sup>	G700050380
<b>Accessory - RF Power Sensor (General)</b>	
Directional power sensor (peak and average power) 300 to 3800 MHz	JD731B
Terminating power sensor (Average Power) 20 to 3800 MHz	JD732B
Directional power sensor (peak and average power) 150 to 3500 MHz	JD733A
Terminating power sensor (peak power) 20 to 3800 MHz	JD734B
Terminating power sensor (average/peak power) 20 to 3800 MHz	JD736B
<b>Accessory - RF Adapters (Connector &amp; Adapters)</b>	
Adapter Type-N(m) to DIN(f), DC to 7.5 GHz, 50 ohm	G700050571
Adapter DIN(m) to DIN(m), DC to 7.5 GHz, 50 ohm	G700050572
Adapter Type-N(m) to SMA(f) DC to 18 GHz, 50 ohm	G700050573
Adapter Type-N(m) to BNC(f), DC to 4 GHz, 50 ohm	G700050574
Adapter Type-N(f) to Type-N(f), DC to 18 GHz 50 ohm	G700050575
Adapter Type-N(m) to DIN(m), DC to 7.5 GHz, 50 ohm	G700050576
Adapter Type-N(f) to DIN(f), DC to 7.5 GHz, 50 ohm	G700050577
Adapter Type-N(f) to DIN(m), DC to 7.5 GHz, 50 ohm	G700050578
Adapter DIN(f) to DIN(f), DC to 7.5 GHz, 50 ohm	G700050579
Adapter Type-N(m) to Type-N(m), DC to 11 GHz 50 ohm	G700050580
Adapter N(m) to QMA(f), DC to 6.0 GHz, 50 ohm	G700050581
Adapter N(m) to QMA(m), DC to 6.0 GHz, 50 ohm	G700050582
Adapter N(m) to 4.1/9.5 MINI DIN (f), DC to 6.0 GHz, 50 ohm	G700050583

Description	Part Number
Adapter N(m) to 4.1/9.5 MINI DIN (m), DC to 6.0 GHz, 50 ohm	G700050584
Adapter N(m) to 4.3-10 (f), DC to 6.0 GHz, 50 ohm	G700050585
Adapter N(m) to 4.3-10 (m), DC to 6.0 GHz, 50 ohm	G700050586
Adapter Type-N(m) to DIN(f), DC to 4 GHz, 50 ohm	G710050571
Adapter N(f) to N(f), DC to 4 GHz, 50 ohm	G710050575
Adapter Type-N(f) to DIN(f), DC to 4 GHz, 50 ohm	G710050577
Adapter Type-N(f) to DIN(m), DC to 7 GHz, 50 ohm	G710050578
<b>Accessory - RF Miscellaneous (General)</b>	
Attenuator 40 dB, 100 W, DC to 4 GHz (unidirectional)	G710050581
Bandpass filter 696 MHz to 716 MHz, N(m) to N(f), 50 ohm	G700050601
Bandpass filter 776 MHz to 788 MHz, N(m) to N(f), 50 ohm	G700050602
Bandpass filter 806 MHz to 849 MHz, N(m) to N(f), 50 ohm	G700050603
Bandpass filter 1710 MHz to 1755 MHz, N(m) to N(f), 50 ohm	G700050604
Bandpass filter 1850 MHz to 1910 MHz, N(m) to N(f), 50 ohm	G700050605
<b>Accessory - General</b>	
USB Bluetooth dongle and dipole antenna 5 dBi	JD70050006
GPS antenna for JD740 and JD780 series	JD71050351
AntennaAdvisor handle19	JD70050007
Cross LAN cable (6ft)	G700550335
USB A to B cable (1.8m)	GC73050515
> 1GB USB memory	GC72450518
Stylus pen	G710550316
<b>Accessory - Battery &amp; Chargers</b>	
Rechargeable lithium ion battery	G710550325
JD700B series AC/DC power adapter_90 W_15 V	JD70050326
Automotive cigarette lighter/12V DC adapter	G710550323
External battery charger	G710550324
<b>Accessory - Manual &amp; Documentation</b>	
JD700B series user's guide - printed version	JD700B362
<b>Accessory - Carrying Case</b>	
Soft carrying case	JD74050341
Hard carrying Case	JD71050342
Hard carrying case with wheels	JD70050342
CellAdvisor backpack carrying case	JD70050343
<b>Optional TAP</b>	
Optical nTAP, three-channel, 50 µm, MM, LC, 50/50 split ratio	TO3-M5-LC-55-K
Optical nTAP, three-channel, 9 µm, SM, LC, 50/50 split ratio	TO3-SM-LC-55-K
<b>Optional SFP Transceiver</b>	
SFP 4G/2G/1G Fibre Channel & 1G Ethernet, 850nm, 150-500m, SX <sup>30</sup>	CSFP-4G-8-1
SFP 4G/ 2G/ 1G Fibre Channel & 1G Ethernet, 1310nm, 5km, LX <sup>30</sup>	CSFP-4G-3-1

## Ordering Information (Continued)

Description	Part Number
SFP 4G/2G/1G Fibre Channel & 1G Ethernet, 1310nm, 20km, LX <sup>30</sup>	CSFP-4G-3-2
SFP+ 8G/4G/2G Fibre Channel, 6G/4.9G CPRI 850 nm MM Multirate <sup>31</sup>	CSFP-PLUS-8G-8-1
SFP+ 8G/4G/2G Fibre Channel, 6G/4.9G CPRI 1310nm SM, 10km <sup>31</sup>	CSFP-PLUS-8G-3-1
SFP+ 1G/10G Ethernet, 1G/10G Fiber Channel & 9.8G CPRI, 850nm, MM, 300m <sup>32</sup>	SFPPLUS-1GE-10GE-8-1
SFP+ 1G/10G Ethernet, 1G/10G Fiber Channel & 9.8G CPRI, 1310nm, SM, 10km <sup>32</sup>	SFPPLUS-1GE-10GE-3-1
<b>Optional StrataSync™</b>	
StrataSync for CellAdvisor RFA - Asset Management-1 Yr	SS-CA-RFA-AM-01
StrataSync for CellAdvisor RFA - Asset Management-2 Yr	SS-CA-RFA-AM-02
StrataSync for CellAdvisor RFA - Asset Management-3 Yr	SS-CA-RFA-AM-03
StrataSync for CellAdvisor RFA - Test Data Management-1 Yr	SS-CA-RFA-TDM-01
StrataSync for CellAdvisor RFA - Test Data Management-2 Yr	SS-CA-RFA-TDM-02
StrataSync for CellAdvisor RFA - Test Data Management-3 Yr	SS-CA-RFA-TDM-03
<b>Optical Power Meters and Fiber Microscope Kits</b>	
USB optical power meter with software, 2.5 and 1.25 mm interfaces, 30-inch USB extender, and carry- ing pouch	MP-60A
USB optical power meter — high power, with software, 2.5 and 1.25 mm interfaces, 30-inch USB extender, and carrying pouch	MP-80A
KIT: FBP-P5000i digital probe, FiberChekPRO software, case, and four tips	FBP-SD101
KIT: FBP-P5000i digital probe, FiberChekPRO software, case, and seven tips	FBP-MTS-101
KIT: FBP-P5000i digital probe, MP-60A USB power meter, FiberChekPRO software, case, tips, and adapters	FIT-SD103
KIT: FBP-P5000i digital probe, MP-60A USB power meter, FiberChekPRO software, case, tips, adapters, and cleaning materials	FIT-SD103-C
KIT: FBP-P5000i digital probe, MP-80A USB power meter, FiberChekPRO software, case, tips, and adapters	FIT-SD113

- Supplied accessories: User's Guide, USB Memory (1GB), Cross LAN Cable, USB Cable, DC car adapter, Li-Ion Battery, AC/DC adapter, Stylus Pen
- Highly recommended using the Calibration Kit (JD78050509, JD78050510, JD70050509)
- Highly recommended using the Calibration Kit (JD78050507, JD78050508) and Bias Tee (option 002)
- Requires option 001
- Needs for RfOFIBER options 060,061,062,063,064,065,070,071,072,073,081,086,101
- Needs Omni or Yagi antenna
- Highly recommended adding option 010
- Includes a Bluetooth USB dongles with 5 dBi dipole antennas (JD70050006)
- Includes a Wi-Fi USB dongle
- Requires G700050380
- Requires option 008, Including Layer2 Term and Monitoring
- Needs proper SFP/SFP+ Transceiver and Optical Tap or thur mode fiber cable (G700050401, G700050402)
- Requires at least one of RfOFIBER Interference Analyzer options (option 060 to 065), needs each of the respective/corresponding Interference Analyzer line rate
- Requires at least one of RfOBSAI Interference Analyzer options (option 070 to 073), needs each of the respective/corresponding Interference Analyzer line rate
- Needs for RfOFIBER measurements (060,061,062,063,064,065,070,071,072,073,081,086,101)
- Needs for option 011
- Needs Proper RF Cables for the inter-connection
- Needs option 050
- Needs G700050366 or G700050367



Contact Us **+1 844 GO VIAVI**  
(+1 844 468 4284)

To reach the Viavi office nearest you,  
visit [viavisolutions.com/contacts](http://viavisolutions.com/contacts).

© 2015 Viavi Solutions Inc.  
Product specifications and descriptions in this  
document are subject to change without notice.  
jd786brfa-ds-cpo-nse-ae  
30175985 901 0616